ADAM-6717 ADAM-6750 ADAM-6760D



Intelligent I/O Gateway with Analog Input, Digital I/O, Solid-State Relay Output (for DC)



ADAM-6717



ADAM-6750



ADAM-6760D

Specifications

Analog Input

Channels Sampling Rate

Resolution

16 bits 0 ~ 150mV, 0 ~ 500mV, Input Range $0 \sim 1V$, $0 \sim 5V$, $0 \sim 10V$,

±150 mV, ±500 mV, ±1V, ±5 V, ±10 V, ±20 mA, 0 ~ 20 mA, 4 ~ 20mA

10 or 100 samples/ second

8 (differential)

(total)

Digital Output

Channels

 Output type channel

Digital Input

Channels

Dry contact

Wet contact

Sink 30 V_{DC} , 0.1A max. per

logic 0: Open logic 1: Close to ground logic 0: 0 ~ 3 VDC or floating

logic 1: 10 ~ 30 V_{DC} Support DO type:

Sink (NPN) and Source (PNP)

Specifications

Digital Input

Channels

Dry contact

Wet contact

support 3KHz counter input logic 0: Open logic 1: Close to ground

logic 0: 0 ~ 3 V_{DC} or floating logic 1: 10 ~ 30 V_{DC}

Support DO type: Sink (NPN) and Source (PNP)

12 (support 3KHz pulse

Digital Output

Channels

output) Output type Sink 30 VDC, 0.1A max. per

channel

Specifications

Digital Input

Channels

support 3KHz counter input Dry contact logic 0: Open

logic 1: Close to ground Wet contact

logic 0: 0 ~ 3 V_{DC} or floating logic 1: 10 ~ 30 V_{DC} Support DO type:

8 (Form A)

Sink (NPN) and Source (PNP)

Relay Output (PhotoMOS SPST)

Channels

 Contact rating $30 V_{DC}$ (Resistive and 1 A @25°C Inductive load) 0.7A @70°C Relay-on time 1.3 ms

Relay-off time 0.8 ms **Peak Load Current** 4A (100ms (1 pulse))

Total Power 400mW / channel

Dissipation

 On-state resistance 0.5Ω

Common Specifications

General

MCU Cortex-A8 32-Bit 1GHz Memory DDR3L 512MB

NAND flash 512MB for Storage system storage microSD Slot (Optional)

08 RT Linux V3.12 **Programming** Node-RED Linux C $10 \sim 30 V_{DC}$ Power input

Operation temperature -40 ~ 70°C

Storage temperature -40 ~ 85°C

Isolation 2500 V_{DC}

Communication

2 x RJ-45 10/100 Mbps LAN port

(2MAC ID) Serial port 2 x RS-485

1 x USB Type-A 2.0, USB port 1 x USB Micro-B 2.0

Ordering information

ADAM-6717-A

ADAM-6750-A

ADAM-6760D-A

Intelligent I/O Gateway with Analog Input Intelligent I/O Gateway with Digital I/O Intelligent I/O Gateway

with Solid-State Relay Output (for DC)